



PART NUMBER	AMP RATING	FREQUENCY	VOLTAGE	WIRE	A	B	C
COR-CDSUW-2010A6-C	DUAL 10A	0 - 60 Hz	120/208VAC	#10	21"	8"	6"
COR-CDSUW-2030A6-C	DUAL 30A	0 - 60 Hz	120/208VAC	#6	22.5"	8"	6"
COR-CDSUW-1060A6-C	60A	0 - 60 Hz	120/208VAC	#6	32"	8"	6"
COR-CDSUW-1100A6-C	100A	0 - 60 Hz	120/208VAC	#2	34"	8"	6"

FILTER SPECIFICATIONS

INSERTION LOSS:

100 DB 14 KHZ TO 10 GHZ WHEN MEASURED IN ACCORDANCE WITH MIL STD 220 FULL LOAD 277 VOLT MAX. LINE TO GROUND 0 TO 60 HZ.

NOTES: IF A DIELECTRIC COUPLING NEEDS TO BE INSTALLED, INSTALL IN CONDUITS CONNECTING TO FILTERS (NOT FURNISHED OR INSTALLED BY REMC)

FILTERS AVAILABLE IN 277/480V, 60Hz AND 120/208V, 400Hz UPON REQUEST

FIELD INSTALLATION

1. CUT HOLE AT REQUIRED LOCATION USING 1 5/16" HOLE SAW.
2. DEBURR METAL AT HOLE.
3. CLEAN AREA AROUND HOLE.
4. CLEAN SMOOTH SURFACE OF FLANGED HEX NUT.
5. INSTALL FILTER WITH FLANGE HEX AGAINST SHIELDING.